KATLAMA YERİ

Panasonic

KNX BINARY INPUT

2-WAY V2.0 WRKT2402-XXX
4-WAY V2.0 WRKT2404-XXX
6-WAY V2.0 WRKT2406-XXX

Kullanma Kılavuzu

654752-P

KATLAMA YERİ

## 1. GENEL ÖZELLİKLER

2-WAY, 4-WAY ve 6-WAY evrensel arabirimleri 2, 4 veya 6 kanallı kuru kontak giriş modülleridir. Ayrıca, cihaza bağlı olarak, LED kontrollü 4 kanallı kuru kontağa konfigüre edilebilir. Sıva altı prizlere monte edilerek konvansiyonel butonlar/anahtarlar ile uyumlu olarak çalışabilirler bu yüzden konvansiyonel anahtarlar KNX sistemi ile entegre edilebilirler.
Telegram tipi (açıkapa - değer) ve kontakların açık veya kapalı durumundaki davranışları ayrı ayrı belirlenebilir.
Cihaz beklemesi verildiğinde girişler aktif hale gelir (cihaz KNX bus hattına bağlı olduğundaki ve konfigürasyonlar ETS programı ile gerçekleştirilir.
Konvansiyonel butonlar, anahtarlar veya gerekli sensörler (zamanlayıcı, alarm sistemi vb.) bağlanabilir.
Kontak voltaj dahili güç kaynağı ile sağlanır, harici gerilim gerektirmez.

### 1.1 2, 4 and 6-Way Binary Input Özellikleri

- Anahtarlama
- 1 ya da 2 buton ile dim edebilme
- 1 ya da 2 buton ile perde-panjur kontrolü
- Dağılım (Yüzde, HVAC, Parlaklık, Sıcaklık, Devrilik, 8 bitlik sayı)
- Panjur değeri
- Sahne
- Komut LED'i (6-Way ile yalnızca C1, C2, C3 ve C4)

1

KATLAMA YERİ

## 2. TEKNİK BİLGİLER

| Genel | |
|---|---|
| Güç kaynağı | Bus gerilimi |
| İzin verilen çalışma sıcaklığı | -5 °C... + 45°C |
| Bus geriliminden çekilen akım değeri | Maks. 10 mA |
| Bus bağlantısı | Bus terminali |
| Koruma tipi | IP 20 - EN 60529 |
| Kirlilik derecesi | 2 - IEC 60664-1 |
| Koruma sınıfı | III - IEC 61140 |
| Aşırı gerilim sınıfı | III - IEC 60664-1 |
| Boyutlar | LxWxH 37 x 37 x 12 (mm) |

2

KATLAMA YERİ

| Girişler | |
|---|---|
| Giriş adedi | 2 Way : 2 giriş<br>4 Way : 4 giriş<br>6 Way : 6 giriş |
| Kontak gerilimi | 3.3 V dahili olarak sağlanır |
| Kontak akımı | 0.1 mA |
| Maksimum kablo uzunluğu | 8 m |
| **LED Çıkışlar** | |
| Çıkış adedi | 2 Way : 2 çıkış<br>4 Way : 4 çıkış<br>6 Way : 6 çıkış |
| Kullanılan | Seri dirençsiz düşük akımlı LED'ler |
| Çıkış akımı | Maksimum 1 mA / çıkış |

3

KATLAMA YERİ

## 3 . BAĞLANTI ŞEMALARI




- Ortak (Aş.(C1)
- Kanal 1 (C1)
- Kanal 2 (C2)
- Ortak (Aş.(C1,C2)
- Kanal 1 (C1)
- Kanal 2 (C2)
- Kanal 3 (C3)
- Ortak (Aş.(C1,C2,C3)
- Kanal 1 (C1)
- Kanal 2 (C2)
- Kanal 3 (C3)
- Ortak (Aş.(C4,C5,C6)
- Kanal 4 (C4)
- Kanal 5 (C5)
- Kanal 6 (C6)

- BLK (Siyah)
- YL (Sarı)
- RD (Kırmızı)
- BLK (Siyah)
- YL (Sarı)
- RD (Kırmızı)
- BU (Mavi)
- BLK (Siyah)
- YL (Sarı)
- RD (Kırmızı)
- BU (Mavi)
- BLK (Siyah)
- BR (Kahverengi)
- RD (Kırmızı)
- GN (Yeşil)

4

KATLAMA YERİ

## GARANTİ KOŞULLARI

- Kullanım kılavuzu ve ürün ile ilgili yazılımlar (varsa) ürün ile birlikte ve sürümü ile birlikte.
- Garanti, garanti süresi içerisinde ve ürünün imalat hatalarından doğup imalatçıya gelebilecek arızaları kapsar.
- Ürünün bütün parçaları dahil olmak üzere, tamamı garanti kapsamındadır (Ürünün ayrılı olduğunun mümkün olmasına bağlı olarak, 6502 sayılı Tüketicinin Korunması Hakkında Kanunun 11. maddesinde yer alan; onarım, yenisinin temin edilmesi, bedelinin iadesi, ayıp oranında bedel indirimi veya sözleşme konusu olan malın ayıbın giderilmesi masrafının satıcıya yüklenmesi hususlarından birini kullanma hakkı.
- Ürünün onarımı veya ürünün yerine yenisinin takılması sırasın ürünün sökülmesi, takılması ve montajı masrafı ile birlikte ürünün yeniden montajı masrafı ve montajı yapılacak yerdeki bağlantılar vahip teknik personel tarafından yapılabilmelidir.
- Yetkili bir bağlantı olmadan yapılan kişilerin montaj ve modifikasyonu sonucunda oluşabilecek arıza. Kaza ve kasıtlıdan tamamı için hiçbir sorumluluk kabul edilmemiş.
- Ürünlerin düşme, kapak ve çerçeve temizliğini kuru veya hafif nemli bez ile yapınız. Alkol, tuğlaya, deterjan vb. kimyasallar kesinlikle kullanılmayınız. Ürün enerji altında iken asla temizlik yapmayınız ve ürünü su ile temas ettirmeyiniz.
- Ürünün başlık kılıdığı yüzeyin boyanması durumunda, ürünün kapak ve çerçevelerini sökerek muhafaza ediniz.
- Yapıma ve montaja uygunda ürünü nemli veya ıslak ortamlardan uzak tutunuz.
- Sıcaklık iç mekan kullanımına göre.

## Panasonic ve Çevre

Panasonic olarak, insanın ve doğa arasında kurulan dengeyi bozan sürdürülebilir yaşama sağlayacağı katkıyı bilincindeyiz. Sürekli inovasyon ve AR-GE çalışmalarımız ile ürünlerimizin tasarımlarımızdan başlayarak üretimi ve kullanımı esnasında çevreyi olumsuz etkilemeyecek malzeme ve teknolojileri - tercih ediyoruz. Enerji ve doğal kaynaklarımızın daha verimli kullanılması için gerekli önlemleri alıyoruz.

Bu sembol dahilinde elektronik ekipmanların ayrı olarak toplanması gerektiğini gösterir.

**Panasonic Müşteri İlişkileri**

Değerli Müşterimiz,

Bizlere kaliteli ürünler sunmak kadar, kaliteli hizmet vermenin de önemine inanıyoruz. Bu sebeple almış olduğunuz ürünlerimiz ile ilgili destek ihtiyacınızda, Panasonic Müşteri İlişkilerine 444 8456 numaralı telefonumuzu arayarak ulaşabilirsiniz.

6

KATLAMA YERİ

Panasonic

Panasonic Life Solutions Elektrik San.ve Tic. A.Ş.
Abdurrahmangazi Mah. Ebubekir Cad. No: 44
34887 Sancaktepe / İstanbul / Türkiye
T: 0(216) 564 55 55 F: 0(216) 564 55 44

DANIŞMA HATTI
444 8456
istr.panasonic.com

KATLAMA YERİ

Panasonic

KNX BINARY INPUT

2-WAY V2.0 WRKT2402-XXX
4-WAY V2.0 WRKT2404-XXX
6-WAY V2.0 WRKT2406-XXX

User Manual

654752-P

KATLAMA YERİ

## 1. GENERAL FEATURES

The KNX universal interfaces 2-WAY, 4-WAY and 6-WAY are binary input modules with 2, 4 or 6 inputs for floating switch/push button contacts binary signals. Furthermore, depending on the device, up to 4 channels can be configured for LED control. The device can be installed in combination with conventional push buttons/switches in flush mounted sockets. This allows integration of conventional switches to KNX system.
The telegram type (switching and value) and the response for dosing and opening the contacts can be specified individually.
The input is activated when voltage is supplied (device is connected to KNX bus) and configuration is done with ETS. Conventional push buttons, switches or any required sensors (timer, alarm system, etc.) can be connected.
Contacts voltage is supplied with integrated power supply, no external voltage required.

### 1.1 Features of The Binary Input 2, 4 and 6-Way

- Switching
- 1 or 2 button Dimming
- 1 or 2 button Shutters/Blinds Control
- Value (Percentage, HVAC, Brightness, Temperature, Priority, 8bit values)
- Value for blinds
- Scene
- Command LED (With 6-WAY only C1,C2,C3 and C4)

1

KATLAMA YERİ

## 2. TECHNICAL INFORMATION

| General | |
|---|---|
| Power supply | Bus voltage |
| Permitted operating temperature | -5 °C... + 45°C |
| Current draw from bus voltage | Max 10 mA |
| Bus connection | Bus terminal |
| Type of protection | IP 20 to EN 60529 |
| Degree of pollution | 2 to IEC 60664-1 |
| Protection class | Class III to IEC 61140 |
| Overvoltage class | Class III to IEC 60664-1 |
| Dimensions | LxWxH 37 x 37 x 12 (mm) |

2

KATLAMA YERİ

| Inputs | |
|---|---|
| Quantity | 2 Way : 2 inputs<br>4 Way : 4 inputs<br>6 Way : 6 inputs |
| Contact voltage | 3.3 V provided internally |
| Contact current | 0.1 mA |
| Maximum cable length | 8 m |
| **LED outputs** | |
| Quantity | 2 Way : 2 outputs<br>4 Way : 4 outputs<br>6 Way : 6 outputs |
| Use | Low current LEDs without series resistor |
| Output current | Maximum 1 mA / output |

3

KATLAMA YERİ

## 3 . CONNECTION DIAGRAMS




- Common (C1,C2)
- Channel 1 (C1)
- Channel 2 (C2)
- Common (C1,C2,C3)
- Channel 1 (C1)
- Channel 2 (C2)
- Channel 3 (C3)
- Common (C4,C5,C6)
- Channel 4 (C4)
- Channel 5 (C5)
- Channel 6 (C6)

- BLK (Black)
- YL (Yellow)
- RD (Red)
- BLK (Black)
- BR (Brown)
- RD (Red)
- BU (Blue)
- BLK (Black)
- YL (Yellow)
- RD (Red)
- BLK (Black)
- BR (Brown)
- RD (Red)
- GN (Green)

4

KATLAMA YERİ

## WARRANTY CONDITIONS

- Warranty period starts as of the delivery date of the product and it is 2 years.
- Warranty covers all the malfunctions likely to occur due to the manufacturing defects of the product and within the warranty period.
- The product including all of its parts is under warranty as a whole. If the product turns out to be defective, the consumer can use one of the following rights stipulated in Article 11 of Consumer Protection Law no. 6502;
  a- Withdrawal from the contract
  b- Demanding discount from sales fee
  c- Demanding the repair
  d- Demanding the replacement of the sold one with a fungible one free from defects.
- In case the consumer chooses the right of free-repair among those rights, the dealer is obliged to repair the product or have the product repaired without claiming any fee under the name of replaced part fee, labor cost or for any other reasons. The consumer can also use the right of free repair against the manufacturer or exporter. The dealer, manufacturer or importer is obliged to deliver the product free of the usage of this right by the consumer.
- In case the consumer uses the right of free repair and if the product
  - fails within the warranty period again and
  - the maximum period required for the repair is exceeded and
  - Authorized service station, dealer, manufacturer or exporter state that it's not possible to repair the product in a way that it will perform its function properly and safely anymore,

  he/she can choose between the right of the refund of the price or the replacement with the one free of defects. If possible, from the dealer. The dealer can not reject the demand of the consumer. In case this demand is not met, the dealer, manufacturer and exporter shall jointly and severally be held responsible.
- The repair period of the product can not exceed 20 business days. This period starts on the notification of the defect to the authorized service station or authorized dealer and ends with the notification of the consumer about the date of delivery of the product to the authorized service station out of warranty period. In case of not eliminating the product malfunction within 10 business days, manufacturer or importer is obliged to dedicate another product with similar characteristics to the use of the consumer until the completion of the product repair. In case the product fails within the warranty period, elapsed time is added to the warranty period.
- The warranty does not cover the following circumstances: Improper use, improper installation, use of determined voltage, current and environmental conditions, damage on the cable connection due to the user's fault and failure of the product due to the facts arising from the fire, flood, earthquake, lightning and similar disasters are not under warranty.
- The consumer can apply to the arbitration committee for consumers or the consumer court where the consumer transaction is made or where the residential area for the disputes to be occurred regarding the usage of the rights arising from the warranty.
- In case the dealer doesn't provide this certificate of warranty, the consumer can apply to the General Directorate of Consumer Protection and Market Surveillance of Ministry of Customs and Trade"

5

KATLAMA YERİ

## WARNING

- Ensure that the power is cut off before the assembly of the products .
- Connection and assembly of the electrical devices should be carried out only by the technical personnel having certificate of competency.
- The manufacturer is assumed free of responsibility for the consequences of the malfunction, accident and loss arising from the improper assembly and use of the products not having the competency certificate.
- Use only a slightly moist cloth to clean the buttons, cover and frame of the product. Never use alcohol, cologne, detergent or other similar chemicals for cleaning. Do not perform wet cleaning.
  do not contact the product with water when the product is energized.
- In case the surface to which the product is connected is dyed, store the product by removing its cover and the frames.
- Keep the product away from the damp or wet environment during the transportation and mapping .
- It is intended for indoor use only.

## Panasonic and Environment

As Panasonic, we are aware of the contribution of a balanced relation established between human and nature to the sustainable life. Thanks to our continuous innovation and R&D studies, we prefer materials and technologies that are not affecting the environment in a negative way during the production and usage of the products starting from the designing phase. We take necessary measures to use energy and natural sources in a more efficient way.

This symbol indicates separate collection of waste electrical and electronic equipment.

**Panasonic Customer Relations**

Dear Customer,

We believe in providing quality service to your as well as offering quality products.
Therefore, you can call 444 8 456 to reach Panasonic customer relations for support regarding the products you purchased.

6

KATLAMA YERİ

Panasonic

Panasonic Life Solutions Elektrik San.ve Tic. A.Ş.
Abdurrahmangazi Mah. Ebubekir Cad. No: 44
34887 Sancaktepe / İstanbul / Turkey
T: 0(216) 564 55 55 F: 0(216) 564 55 44

HOTLINE
444 8456
istr.panasonic.com